#### Datasheet

### **19-inch Single-phase Safety PDU** Power distribution unit for test equipment

#### DIST-16AM-192U-01

TAME-T

### **DESCRIPTION**

The 2U Rack Units Single-phase power distributor developed by Tame-Test mainly provides power to the electrical and electronic test instruments racked inside the 19-inch cabinets. It is designed to supply European standard 230 Volts (50Hz) AC, the plug-in PDU has also 24 V DC terminals designed for the low power devices. The PDU comes with all necessary features to ensure the safety of people and the powered equipment as well.

The PDU includes a sequential startup used to limit current draws by powering 3 groups of 4 outlets one by one. The PDU is equipped with two dry contact thermostats inputs to control the temperature in the test benches, allowing a pre-alarm and a total shutdown of all output outlets.

An Emergency Power-Off (EPO) button is placed in the front panel to disconnect the PDU from the main power source for safety matters. The EPO is exported to back panel to turn off any inverter if it is used in the test platform.



## **KEY ADVANTAGES**

- Rack mountable in all 19-inch test benches
- CE Certified
- Easy to install in customer applications
- Alert and emergency stop system according to temperature status

## **FEATURES**

- EIA-310 compliant 19 in. rack, 2U height
- 2 IEC 60320-C13 permanent AC outlets
- 12 IEC 60320-C13 sequential AC outlets
- 24 VDC power outlet
- 230 VAC 1-phase mains input
- 2 Inputs for temperature control
- Emergency Power-Off button according to IEC 60947-5-1 and IEC 60204-1
- Emergency stop function according to temperature status

- LED for line presence
- LED for temperature status
- Main switch ON/OFF
- Mains fuses
- Residual current circuit breaker according to IEC 61008-1 and IEC 62423
- CE certified
- Electro Magnetic Compatibility directive compliant
- Low Voltage directive compliant

### Datasheet 19-inch Single-phase Safety PDU Power distribution unit for test equipment



DIST-16AM-192U-01

# **TECHNICAL SPECIFICATIONS**

#### ELECTRICAL DATA

Power Phase	1-phase
Voltage Rating	220 – 240 V AC
Frequency Rating	50-60 Hz
Current Rating	16 A
Max Current per outlet	Up to 16 A
AC Outlets	12 Sequential + 2 Permanent
DC Terminals	+24 V DC / 1.5 A
Electrical voltage indi- cator	White
Trip Sensitivity	min. 30 mA

#### MECHANICAL DATA

Width	19-inch 482,6mm
Height	2 U (88,9 mm)
Depth	340 mm
Weight	5 kg



### SAFETY FEATURES

Designation	Power-up	Turn-off
XP1, XP2	Permanent	Emergency stop or T2 or circuit breaker 30 mA
ХРЗ - ХР6	When pressing button 🅕	Press button O or Emergency stop or T2 or circuit breaker 30 mA
XP7 - XP10	When pressing button 🅕	Press button 🗿 or Emergency stop or T2 or circuit breaker 30 mA
XP11 - XP14	When pressing button 🕕	Press button or Emergency stop or T2 or circuit breaker 30 mA

## Color code of the temperature monitoring indicator

Green : temperature below the first threshold: all outlets are activated Orange : temperature between the first and second thresholds: all outlets are activated Red : temperature above the second threshold: all outlets are deactivated

Tame-Test - TRONICO Group - 26 rue du Bocage - 85660 Saint-Philbert-de-Bouaine (France) +33 (0)2 51 41 91 35 - contact@tame-test.com - <u>www.tame-test.com</u> All the information contained in this document is the exclusive property of TRONICO and cannot be reproduced nor communicated with a third party without the express written authorization of TRONICO. TRONICO reserves the right to make any changes without prior notice. Tame-Test is a registered trademark of TRONICO. STRICTLY CONFIDENTIAL TRONICO

#### Datasheet

**19-inch Single-phase Safety PDU** Power distribution unit for test equipment



DIST-16AM-192U-01

F

#### PRODUCT REAR VIEW



Designation	Connector Type	Configurations
XP1, XP2	IEC C13	Permanent outlets
XP3, XP4, XP5, XP6, XP7, XP8, XP9, XP10, XP11, XP12, XP13, XP14	IEC C13	Sequential outlets (outlet banks)
XP0	Powercon	Mains inlet 230 V AC/50 Hz
XP15	8-point screw terminal	<ul> <li>UPS of the inverter</li> <li>DC 24 V/1,5A Output</li> <li>T1/T2 NO Thermostat Inputs</li> <li>Output indicating that temperature has been exceeded (1st threshold)</li> </ul>
хто	Screw	Grounding terminal

### PRODUCT FRONT VIEW

	Interrupteur différentiel Differential switch ©	Fusibles Fuses F1 - 18A © F2 - 18A	Secteur Marche / Arrét Statut T T'Status
Туре			Description
Differential switch			Protection against power leakage
Fuses F1, F2			Protection against short-circuits, 16A
Inlet / Line			Indicator of electrical voltage presence: white
On / off			ON/OFF Push button
T° Status			Indicator of temperature status: Green, Orange, Red
Safety function			Emergency power off button

Tame-Test - TRONICO Group - 26 rue du Bocage - 85660 Saint-Philbert-de-Bouaine (France) +33 (0)2 51 41 91 35 - contact@tame-test.com - <u>www.tame-test.com</u> All the information contained in this document is the exclusive property of TRONICO and cannot be reproduced nor communicated with a third party without the express written authorization of TRONICO. TRONICO reserves the right to make any changes without prior notice. Tame-Test is a registered trademark of TRONICO. STRICTLY CONFIDENTIAL TRONICO